

MOSFET - N-Channel, POWERTRENCH®

80 V, 100 A, 3.9 m Ω

FDMS039N08B

General Description

This N-Channel MOSFET is produced using **onsemi**'s advance POWERTRENCH process that has been tailored to minimize the on-state resistance while maintaining superior switching performance.

Features

- Max $R_{DS(on)} = 3.2 \text{ m}\Omega$ (Typ.) @ $V_{GS} = 10 \text{ V}$, $I_D = 50 \text{ A}$
- Low FOM R_{DS(on)} * Q_G
- Low Reverse Recovery Charge, $Q_{rr} = 80 \text{ nC}$
- Soft Reverse Recovery Body Diode
- Enables Highly Efficiency in Synchronous Rectification
- Fast Switching Speed
- 100% UIL Tested
- This Device is Pb-Free, Halide Free and is RoHS Compliant

Applications

- Synchronous Rectification for ATX / Server / Telecom PSU
- Battery Protection Circuit
- Motor Drives and Uninterruptible Power Supplies

MOSFET MAXIMUM RATINGS (T_C = 25°C, unless otherwise noted)


Symbol	Parameter	FDMS039N08B	Unit
V_{DSS}	Drain to Source Voltage	80	V
V_{GSS}	Gate to Source Voltage	±20	V
Ι _D	Drain Current - Continuous (T _C = 25°C) - Continuous (T _A = 25°C) (Note 1a)	100 19.4	А
I _{DM}	Drain Current - Pulsed (Note 2)	400	mJ
E _{AS}	Single Pulse Avalanche Energy (Note 3)	240	mJ
P _D	Power Dissipation $(T_C = 25^{\circ}C)$ $(T_A = 25^{\circ}C)$ (Note 1a)	104 2.5	W
T _J , T _{STG}	Operating and Storage Temperature Range	-55 to +150	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

THERMAL CHARACTERISTICS (T_C = 25°C, unless otherwise noted)

Symbol	Parameter	FDMS039N08B	Unit
$R_{\theta JC}$	Thermal Resistance, Junction to Case	1.2	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient (Note 1a)	50	

V _{DSS}	R _{DS(on)} MAX	I _D MAX
80 V	$3.9~\mathrm{m}\Omega~@~10~\mathrm{V}$	100 A




PQFN8 5X6, 1.27P (Power 56) CASE 483AE

MARKING DIAGRAM

&Z&3&K FDMS 039N08B

&Z = Assembly Plant Code &3 = 3-Digit Date Code &K = 2-Digits Lot Run Code FDMS039N08B = Specific Device Code

PIN ASSIGNMENT



ORDERING INFORMATION

See detailed ordering and shipping information on page 7 of this data sheet.

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)

Symbol	Parameter	Test Condition	Min	Тур	Max	Unit
OFF CHAR	ACTERISTICS				•	
BV _{DSS}	Drain to Source Breakdown Voltage	$I_D = 250 \mu A, V_{GS} = 0 V$	80	-	_	V
$\Delta {\sf BV}_{\sf DSS}$ / $\Delta {\sf T}_{\sf J}$	Breakdown Voltage Temperature Coefficient	I_D = 250 μA, Referenced to 25°C	-	0.04	-	V/°C
I _{DSS}	Zero Gate Voltage Drain Current	V _{DS} = 64 V, V _{GS} = 0 V	_	-	1	μΑ
I _{GSS}	Gate to Body Leakage Current	$V_{GS} = \pm 20 \text{ V}, V_{DS} = 0 \text{ V}$	_	-	±100	nA
ON CHARA	CTERISTICS					
V _{GS(th)}	Gate Threshold Voltage	$V_{GS} = V_{DS}, I_D = 250 \mu A$	2.5	_	4.5	V
R _{DS(on)}	Static Drain to Source On Resistance	V _{GS} = 10 V, I _D = 50 A	_	3.2	3.9	mΩ
9FS	Forward Transconductance	V _{DS} = 10 V, I _D = 50 A	_	100	_	S
DYNAMIC C	CHARACTERISTICS					
C _{iss}	Input Capacitance	V _{DS} = 40 V, V _{GS} = 0 V	_	5715	7600	pF
C _{oss}	Output Capacitance	f = 1 MHz	_	881	1170	pF
C _{rss}	Reverse Transfer Capacitance	1	_	15	_	pF
C _{oss} (er)	Engry Releted Output Capacitance	V _{DS} = 40 V, V _{GS} = 0 V	-	1646	_	pF
Q _{g(tot)}	Total Gate Charge at 10 V	$V_{DS} = 40 \text{ V}, I_{D} = 50 \text{ A } V_{GS} = 0 \text{ V to } 10 \text{ V}$ (Note 4)	_	77	100	nC
Q _{gs}	Gate to Source Gate Charge		_	34	_	nC
Q _{gs2}	Gate Charge Threshold to Plateau		_	13	_	nC
Q _{gd}	Gate to Drain "Miller" Charge	1	_	16	-	nC
ESR	Equivalent Series Resistance	f = 1 MHz	_	1.2	_	Ω
SWITCHING	CHARACTERISTICS					
t _{d(on)}	Turn-On Delay Time	$V_{DD} = 40 \text{ V}, I_{D} = 50 \text{ A V}_{GS} = 10 \text{ V},$	_	42	94	ns
t _r	Turn-On Rise Time	$R_G = 4.7 \Omega \text{ (Note 4)}$	_	25	60	ns
t _{d(off)}	Turn-Off Delay Time	1	_	48	106	ns
t _f	Turn-Off Fall Time	1	_	17	44	ns
DRAIN-SOL	JRCE CHARACTERISTICS					
I _S	Maximum Continuous Drain to Source Diode Forward Current		_	_	100	Α
I _{SM}	Maximum Pulsed Drain to Source Diode Forward Current		-	-	400	Α
V _{SD}	Drain to Source Diode Forward Voltage	V _{GS} = 0 V, I _{SD} = 50 A	-	-	1.3	V
t _{rr}	Reverse Recovery Time	V _{GS} = 0 V, I _{SD} = 50 A, V _{DD} = 40 V	-	68	_	ns
Q _{rr}	Reverse Recovery Charge	dI _F /dt = 100 A/μs	-	80	_	nC

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

1. R_{θJA} is determined with the device mounted on a 1 in² pad 2 oz copper pad on a 1.5 x 1.5 in. board of FR-4 material. R_{θJC} is guaranteed by design while $R_{\theta CA}$ is determined by the user's board design.



a. 50°C/W when mounted on a 1 in² pad of 2 oz copper.



b. 125°C/W when mounted on a minimum pad of 2 oz copper.

- 2. Repetitive rating: pulse-width limited by maximum junction temperature.
- L = 0.3 mH, I_{AS} = 40 A, starting T_J = 25°C.
 Essentially independent of operating temperature typical characteristics.

TYPICAL PERFORMANCE CHARACTERISTICS

I_D, Drain Current (A)




Figure 1. On-Region Characteristics




Figure 2. Transfer Characteristics




Figure 3. On–Resistance Variation vs. Drain Current and Gate Voltage




Figure 4. Body Diode Forward Voltage Variation vs. Source Current and Temperature




Figure 5. Capacitance Characteristics




Figure 6. Gate Charge Characteristics

V_{GS}, Gate-Source Voltage (V)

TYPICAL PERFORMANCE CHARACTERISTICS (continued)




Figure 7. Breakdown Voltage Variation vs. Temperature




Figure 8. On-Resistance Variation vs. Temperature




Figure 9. Maximum Safe Operating Area




Figure 10. Maximum Drain Current vs. Case Temperature




Figure 11. Unclamped Inductive Switching Capability




Figure 12. Eoss vs. Drain to Source Voltage

TYPICAL PERFORMANCE CHARACTERISTICS (continued)




Figure 13. Transient Thermal Response Curve




Figure 14. Gate Charge Test Circuit & Waveform




Figure 15. Resistive Switching Test Circuit & Waveforms




Figure 16. Unclamped Inductive Switching Test Circuit & Waveforms




Figure 17. Peak Diode Recovery dv/dt Test Circuit & Waveforms

PACKAGE MARKING AND ORDERING INFORMATION

Device	Device Marking	Package	Reel Size	Tape Width	Shipping [†]
FDMS039N08B	FDMS039N08B	PQFN8 5X6, 1.27P (Power 56) (Pb–Free, Halide Free)	13"	12 mm	3000 / Tape & Reel

[†]For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

POWERTRENCH is registered trademark of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries.

PKG &

PIN 1

AREA






В

DATE 21 JAN 2022


NOTES:

- 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
- 2. CONTROLLING DIMENSION: MILLIMETERS
- 3. COPLANARITY APPLIES TO THE EXPOSED PADS AS WELL AS THE TERMINALS.
- 4. DIMENSIONS D1 AND E1 DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR GATE BURRS.
- 5. SEATING PLANE IS DEFINED BY THE TERMINALS. "A1" IS DEFINED AS THE DISTANCE FROM THE SEATING PLANE TO THE LOWEST POINT ON THE PACKAGE BODY.
- 6. IT IS RECOMMENDED TO HAVE NO TRACES OR VIAS WITHIN THE KEEP OUT AREA.




OPTIONAL DRAFT

L2· SEATING **DETAIL B DETAIL C** PLANE SCALE: 2:1 SCALE: 2:1



SIDE VIEW



*FOR ADDITIONAL INFORMATION ON OUR PB-FREE STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLOAD THE ON SEMICONDUCTOR SOLDERING AND MOUNTING TECHNIQUES REFERENCE MANUAL, SOLDERRM/D.

RECOMMENDATION

DIM	MILLIMETERS				
Diwi	MIN.	NOM.	MAX.		
Α	0.90	1.00	1.10		
A1	0.00	-	0.05		
b	0.21	0.31	0.41		
b1	0.31	0.41	0.51		
А3	0.15	0.25	0.35		
D	4.90	5.00	5.20		
D1	4.80	4.90	5.00		
D2	3.61	3.82	3.96		
Е	5.90	6.15	6.25		
E1	5.70	5.80	5.90		
E2	3.38	3.48	3.78		
E3	(0.30 REF			
E4	(0.52 REF			
е	,	1.27 BSC	;		
e/2	Ū	0.635 BS	С		
e1	• •	3.81 BSC	;		
e2	Ú	0.50 REF			
L	0.51	0.66	0.76		
L2	0.05	0.18	0.30		
L4	0.34	0.44	0.54		
Z	0.34 REF				
θ	0°	_	12°		

DOCUMENT NUMBER:	EUMENT NUMBER: 98AON13655G Electronic versions are uncontrolled except when accessed directly from the Document Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in re-		
DESCRIPTION:	PQFN8 5X6, 1.27P		PAGE 1 OF 1

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI., and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems. or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales