Vishay High Power Products

Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED Pt^{TM}



SHA

PRODUCT SUMMARY				
V _F (typical)	0.96 V			
I _{F(AV)}	8 A			
V _R	600 V			

FEATURES

- Benchmark ultralow forward voltage drop
- Hyperfast recovery time
- Low leakage current
- 175 °C operating junction temperature
- · Designed and qualified for industrial level

DESCRIPTION

State of the art, ultralow V_F , soft-switching hyperfast rectifiers optimized for Discontinuous (Critical) Mode (DCM) Power Factor Correction (PFC).

The minimized conduction loss, optimized stored charge and low recovery current minimize the switching losses and reduce over dissipation in the switching element and snubbers.

The device is also intended for use as a freewheeling diode in power supplies and other power switching applications.

APPLICATIONS

AC-DC SMPS 70 W to 400 W

e.g. laptop and printer AC adaptors, desktop PC, TV and monitor, games units and DVD AC-DC power supplies.

ABSOLUTE MAXIMUM RATINGS					
PARAMETER	SYMBOL	TEST CONDITIONS	MAX.	UNITS	
Peak repetitive reverse voltage	V _{RRM}		600	V	
Average rectified forward current	I _{F(AV)}	T _C = 160 °C	8		
Non-repetitive peak surge current	I _{FSM}	T _J = 25 °C	175	А	
Peak repetitive forward current	I _{FM}		16		
Operating junction and storage temperatures	T _J , T _{Stg}		- 65 to 175	°C	

ELECTRICAL SPECIFICATIONS (T _J = 25 °C unless otherwise specified)							
PARAMETER	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNITS	
Breakdown voltage, blocking voltage	V _{BR} , V _R	I _R = 100 μA	600	-	-		
	I _F = 8 A	-	0.96	1.05	V		
Forward voltage V _F		I _F = 8 A, T _J = 150 °C	-	0.81		0.86	
Reverse leakage current I _R		$V_{R} = V_{R}$ rated	-	0.05	5	μA	
		$T_J = 150 \ ^{\circ}C, \ V_R = V_R \ rated$	-	20	100		
Junction capacitance	CT	V _R = 600 V	-	17	-	pF	
Series inductance	L _S	Measured lead to lead 5 mm from package body		8.0	-	nH	

Vishay High Power Products

Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED PtTM



DYNAMIC RECOVERY CHARACTERISTICS ($T_c = 25 \text{ °C}$ unless otherwise specified)							
PARAMETER	SYMBOL	TEST CONDITIONS		MIN.	TYP.	MAX.	UNITS
	t _{rr}	$I_F = 1 \text{ A}, \text{ d}I_F/\text{d}t = 10$	00 A/µs, V _R = 30 V	-	60	100	
Bayaraa raaayan tima		$I_F = 8 \text{ A}, dI_F/dt = 100 \text{ A}/\mu\text{s}, V_R = 30 \text{ V}$		-	150	250	
Reverse recovery time		T _J = 25 °C	I _F = 8 A dI _F /dt = 200 A/μs V _R = 390 V	-	170	-	ns
		T _J = 125 °C		-	250	-	
Peak recovery current	I _{RRM}	T _J = 25 °C		-	15	-	A
		T _J = 125 °C		-	20	-	
Reverse recovery charge Q _{rr}	0	T _J = 25 °C		-	1.3	-	μC
	Qrr	T _J = 125 °C		-	2.6	-	

THERMAL - MECHANICAL SPECIFICATIONS							
PARAMETER	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNITS	
Maximum junction and storage temperature range	T _J , T _{Stg}		- 65	-	175	°C	
Thermal resistance, junction to case per leg	R _{thJC}		-	1.4	2		
Thermal resistance, junction to ambient per leg	R _{thJA}	Typical socket mount	-	-	70	°C/W	
Thermal resistance, case to heatsink	R _{thCS}	Mounting surface, flat, smooth and greased	-	0.5	-	-	
			-	2.0	-	g	
Weight			-	0.07	-	OZ.	
Mounting torque			6.0 (5.0)	-	12 (10)	kgf ⋅ cm (lbf ⋅ in)	
		Case style D ² PAK		8ETL06S			
Marking device		Case style TO-262		8ETL06-1			



Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED Pt^{TM}

Vishay High Power Products





Fig. 2 - Typical Values of Reverse Current vs. Reverse Voltage



Fig. 3 - Typical Junction Capacitance vs. Reverse Voltage



Fig. 4 - Maximum Thermal Impedance Z_{thJC} Characteristics

Vishay High Power Products

Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED Pt[™]







Note

 $^{(1)} \mbox{ Formula used: } T_C = T_J - (Pd + Pd_{REV}) \ x \ R_{thJC}; \\ Pd = \mbox{ Forward power loss } = I_{F(AV)} \ x \ V_{FM} \ at \ (I_{F(AV)}/D) \ (see \ fig. \ 6); \\ Pd_{REV} = \mbox{ Inverse power loss } = V_{R1} \ x \ I_R \ (1 - D); \ I_R \ at \ V_{R1} = \ Rated \ V_R$



SHAY

Fig. 7 - Typical Reverse Recovery Time vs. dl_F/dt



Fig. 8 - Typical Stored Charge vs. dl_F/dt



Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED Pt^{TM}

Vishay High Power Products





Fig. 9 - Reverse Recovery Parameter Test Circuit



Fig. 10 - Reverse Recovery Waveform and Definitions



Vishay High Power Products

Ultralow V_F Hyperfast Rectifier for Discontinuous Mode PFC, 8 A FRED Pt^{TM}

ORDERING INFORMATION TABLE



LINKS TO RELATED DOCUMENTS				
Dimensions http://www.vishay.com/doc?95014				
Part marking information http://www.vishay.com/doc?95008				
Packaging information	http://www.vishay.com/doc?95032			

6

www.vishay.com



Vishay

Disclaimer

All product specifications and data are subject to change without notice.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained herein or in any other disclosure relating to any product.

Vishay disclaims any and all liability arising out of the use or application of any product described herein or of any information provided herein to the maximum extent permitted by law. The product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein, which apply to these products.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications unless otherwise expressly indicated. Customers using or selling Vishay products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify Vishay for any damages arising or resulting from such use or sale. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

Product names and markings noted herein may be trademarks of their respective owners.